

# Binary Coded Decimal

Last updated 11/29/22

These slides introduce binary coded decimal number concepts

# Binary Coded Decimal

- Binary Coded Decimal (BCD)
  - No negative representation
  - Used in some financial applications

# Binary Coded Decimal

- Bit values
- Encode base 10 digits into 4 bit nibbles

50	→	0101 0000
79	→	0111 1001

# Binary Coded Decimal

- Convert decimal to BCD

convert 37 decimal to BCD

4 bits → bit values of            8 | 4 | 2 | 1

3 → 0011                    0 0 1 1

7 → 0111                    0 0 1 1 0 1 1 1

37        →                    0011 0111 BCD

# Binary Coded Decimal

- Convert BCD to decimal

convert 10010110 BCD to decimal

Break into 4 bit nibbles

10010110      →      1001   0110

1001 → 9

0110 → 6

10010110 BCD → 96



# Binary Coded Decimal

- Limits
- Maximum values:

- 4 bits = 9
- 8 bits = 99
- 16 bits = 9999

9	8	7	6	5	4	3	2	1	0
1001	1000	0111	0110	0101	0100	0011	0010	0001	0000

# Binary Coded Decimal

- Issues
  - No negative values
  - Not efficient – limited range

9	8	7	6	5	4	3	2	1	0
1001	1000	0111	0110	0101	0100	0011	0010	0001	0000